



STICK-ON[®] SERIES


Model STA-2

High Output Line Amplifiers

ANYWHERE YOU NEED...

- Up to 24 dB Gain in an Audio Line
- Conversion from Unbalanced to Balanced
- Conversion from High to Low impedance
- Low Impedance, High Current Line Drivers
- A Two-channel Line-Level Preamplifier
- High Gain, High Output, High Performance

You Need The STA-2!



The STA-2 is part of a group of products in the STICK-ON series from Radio Design Labs. The durable bottom adhesive permits quick, permanent or removable mounting nearly anywhere or it may be used with RDL's racking accessories. The STA-2 offers the ultimate in high performance line-level preamplification, with the big *plus*, you can put it right where you need it!

APPLICATION: The STA-2 is a two channel, line-level audio preamplifier. Each channel is identical. The audio inputs are bridged at 5 k Ω and accept either an unbalanced or a balanced audio signal. Gain is adjustable from unity gain to +24 dB using a 25-turn precision trimming potentiometer. The output line driver circuits are designed to drive long balanced audio lines into 600 Ω loads.

The audio circuits in the STA-2 are all dc coupled for the ultimate in pure, transparent audio clarity. The power supply input may be fed from a floating (not ground-referenced) 24 Vdc power source, or from a bipolar power supply (+/-12 Vdc or +/-15 Vdc).

Many audio products provide optimum performance when feeding into a bridging input, but may not provide the output needed to directly drive low-impedance lines terminated with 600 Ω transformers. The STA-2 is specifically designed for such installations, and is also ideal in installations requiring high gain in line-level audio transmission.

Both the input and output circuits function as electronic transformers, permitting either balanced or unbalanced audio connections. The STA-2 may be used as a balanced input/balanced high-level output, two-channel (stereo) preamplifier, or may be used to convert unbalanced sources to 600 Ω balanced lines.

In installations where high gain may be required and balanced signals must drive terminated 600 Ω lines, the STA-2 is the ultimate choice. The STA-2 offers the unparalleled longevity and audio clarity for which RDL products are known. Used in conjunction with other RDL RACK-UP[®], STICK-ON, TX[™], or FLAT-PAK[™] series products, the STA-2 can be the foundation for many high quality, innovative audio systems!




STICK-ON® SERIES

Model STA-2

High Output Line Amplifiers

Installation/Operation

EN55103-1 E1-E5; EN55103-2 E1-E4
 Typical Performance reflects product at publication time exclusive of EMC data, if any, supplied with product. Specifications are subject to change without notice.



(NOTE: STA-2 Connections are identical to those of STA-1)

TYPICAL PERFORMANCE

Amps per STA-2:

Gain:

Input impedance:

Input configuration:

Output impedance:

Output configuration:

Frequency Response:

Total Harmonic Distortion:

Output Level:

Headroom:

Noise:

CMRR:

Crosstalk:

Power Requirement:

2 identical circuits (stereo or dual mono operation)

Unity to 24 dB adjustable, into 600 Ω (separate controls for each channel)

5 kΩ bridging

Balanced or unbalanced

150Ω balanced, drives 600Ω or 10kΩ lines

Balanced or unbalanced

10 Hz to 50 kHz +/- 0.25 dB

< 0.020%

+4 dBu

18 dB (at rated output level of +4 dBu)

-80 dB referred to 4 dBu (20 Hz to 20 kHz)

-65 dB at 100 Hz

Better than 80 dB (10 Hz to 20 kHz)

24 to 33 Vdc @ 50 mA, Floating

Radio Design Labs Technical Support Centers

U.S.A. (800) 933-1780, (928) 778-3554; Fax: (928) 778-3506

Europe [NH Amsterdam] (+31) 20-6238 983; Fax: (+31) 20-6225-287